

Hardware compatibility list for HiPath 33xx and 35xx boards

updated: 18.05.2009

| | | Board for System: | | | | HP3000 SW-Version | | | | | | |
|--|---|-------------------|------|------------|---|-------------------|------|------|------|------|------|----|
| Board | Part Number | 3350 | 3550 | 3300 (19") | | V1.2 | V3.0 | V4.0 | V5.0 | V6.0 | V7.0 | V8 |
| | | | | | | | | | | | | |
| CBCC Motherboard | S30810-Q2935-A201 Ab Zust. G2 für 64MB MMC (as of issue number G2 for 64MB MMC) | x | x | - | - | X | X | X | no | no | no | no |
| CBCC Motherboard Ringing voltage (a/b) 35 V | S30810-K2935-A301 Ab Zust. D1 für 64MB MMC (as of issue number D1 for 64MB MMC) | x | x | - | - | no | no | no | X | X | X | X |
| CBCC new LIM and EVM integrated, 1 x V24 Ringing voltage (a/b) 65 V, CLIP | S30810-K2935-A401 | x | x | - | - | | | | X | X | X | X |
| CMA Clock Modul ADPCM | S30807-Q6931-X | x | x | x | x | no | no | no | X | X | X | X |
| CMS Clock Module Small (Required for Cordless Office and networking) | S30807-Q6928-X | x | x | x | x | X | X | X | X | X | X | X |
| LIM LAN-Interface Module | S30807-Q6930-X | x | x | x | x | X | X | X | X | X | X | X |
| MMC16 Multimedia card | | x | x | x | x | X | X | X | no | no | no | no |
| MMC64 Multimedia card | S30122-X8002-X10 | x | x | x | x | no | no | no | X | X | X | X |
| MMC128 Multimedia card | S30122-X8002-X25 | x | x | x | x | no | no | no | X | X | X | X |
| PSUP Power Supply Unit Point | S30122-K5658-M | x | - | - | - | X | X | X | X | X | X | X |
| UPSC-D Power supply | S30122-K5660-M300 | x | x | - | - | X | X | X | X | X | X | X |
| UPSC-DR Power supply | S30122-K7373-M900 | - | - | x | x | | | X | X | X | X | X |
| ALUM4 Trunk Loop Power Failure Transfer | S30817-H935-M | x | x | - | - | X | X | X | X | X | X | X |
| ANI4 Automatic Number Identification | S30807-H6917-Axxx (for selected countries only) | x | x | - | - | X | X | X | X | X | X | X |
| ANI4R | S30810-K2953-X2xx (for selected countries only) | - | - | x | x | | | X | X | X | X | X |
| EXM For connecting an external music source | S30817-H902-B401 | x | x | - | - | X | X | X | X | X | X | X |
| EXMR For connecting an external music source | S30122-X7403-T | x | x | x | x | X | X | X | X | X | X | X |

| | | | | | | | | | | | | |
|--|--|---|---|---|---|----|----|----|----|-------------------------------|---------------------------|----|
| GEE12 | S30817-Q951-Axxx country variants | x | x | - | - | X | X | X | X | X | X | X |
| GEE 4 16KHz Call metering (for TLA) | S30817-H951-M313 | x | x | - | - | X | X | X | X | X | X | X |
| UAM Announcement before Answering | (Ländervarianten) country variants | x | x | - | - | X | X | X | X | X | X | X |
| OPAL Options Adapter Long | C39195-A7001-B130 | x | x | - | - | X | X | X | X | X | X | X |
| STBG4 (For France only) | S30817-Q934-A | x | x | - | - | X | X | X | X | X | X | X |
| STRB Actors/Sensors | S30817-Q932-A | x | x | - | - | X | X | X | X | X | X | X |
| V24/1 V24/1 interface (not for CBCC -A401) | S30807-Q6916-X100 | x | x | - | - | X | X | X | X | X | X | X |
| IVMS8 8 ports Integrated voice mail for 3550 | S30122-Q7379-X | - | x | - | - | X | X | X | X | X | X | X |
| IVMS8N (8 Port) new Integrated voice mail for 3350/3550 (with hard disc) | S30122-K7379-X200 | x | x | - | - | no | no | no | no | X | X | X |
| IVMP8 Integrated voice mail for 3350 | S30122-Q7379-X100 | x | - | - | - | X | X | X | X | X | X | X |
| IVMP4 (4 Port) Integrated voice mail for 3350/3550 (without hard disc) | S30122-Q7721-X | x | x | - | - | no | no | no | no | X | X | X |
| EVM , Entry Voice Mail for CBCC S30810-K2935-A301/ A401 CBRC S30810-K2935-Z301/ Z401 | S30807-Q6945-X | x | x | x | x | no | no | no | X | X | X | X |
| SLU8 Digitale Subscriber Line (U _{PN}) | S30817-Q922-A301 | x | x | - | - | X | X | X | X | X | X | X |
| 4SLA Subscriber Line Analog Ringing voltage (a/b) 75 V | S30810-H2923-X200 | x | x | - | - | X | X | X | X | X | X | X |
| SLAD4 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF- | S30810-H2956-X100 | x | x | - | - | no | no | no | no | X V6.0R11.1.0, bind 831 | X V7R4.3.0, bind 42 | X |
| 8SLA Subscriber Line Analog Ringing voltage (a/b) 75 V | S30810-H2923-X100 | x | x | - | - | X | X | X | X | X | X | X |
| SLAD8 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF- receiver | S30810-H2956-X200 | x | x | - | - | no | no | no | no | X V6.0R11.1.0, bind 831 | X V7R4.3.0, bind 42 | X |
| 16SLA Subscriber Line Analog Ringing voltage (a/b) 75 V | S30810-H2923-X | x | x | - | - | X | X | X | X | X | X | X |
| SLAD16 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF- receiver, planned in Sept. 09 | S30810-H2957-X | x | x | - | - | no | no | no | no | open | X | X |
| HXGS LAN-Board | S30810-Q2931-X | x | x | - | - | X | X | X | no | no | no | no |
| HXGS2 LAN-Board HG1500 V2 | S30810-Q2939-X | x | x | - | - | X | X | X | no | no | no | no |

| | | | | | | | | | | | | |
|--|--|---|---|---|---|----|------|------|------|---------|------|----|
| HXGS3 LAN-Board HG1500 V3 | S30810-Q2943-X | x | x | - | - | no | V3.0 | V3.0 | V5.0 | V6.0 | V7.0 | V8 |
| HXGS3 (new as of V8) LAN-Board HG1500 V3 | S30810-Q2943-X1 | x | x | - | - | no | no | no | V8 | V8 | V8 | V8 |
| PDM1 extension module for HXGS3/HXGR3 | S30807-Q5692-X100 | x | x | x | x | no | X | X | X | X | X | X |
| STLS2 S0-Trunk- / Subscriber Line | S30817-Q924-B313 | x | x | - | - | X | X | X | X | X | X | |
| STLSX2 new S0-Trunk- / Subscriber Line | S30810-H2944-X100 | x | x | - | - | no | no | no | X | X | X | X |
| STLS4 S0-Trunk- / Subscriber Line | S30817-Q924-A313 | x | x | - | - | X | X | X | X | X | X | |
| STLSX4 new S0-Trunk- / Subscriber Line | S30810-H2944-X | x | x | - | - | no | no | no | X | X | X | X |
| TLA2 Analog Trunk Line | S30817-H923-B313 = Germany S30817-H923-Bxx = Country var. | x | x | - | - | X | X | X | X | X | X | |
| TLANI2 new Analog Trunk with CLIP | S30810-Q2953-X100 = Germany S30810-Q2953-X1xx = Country | x | x | - | - | no | no | no | no | R10.0.0 | X | X |
| TLA4 Analog Trunk Line | S30817-H923-A313 = Germany S30817-H923-Axx = Country var. | x | x | - | - | X | X | X | X | X | X | |
| TLANI4 new Analog Trunk with CLIP | S30810-Q2953-X = Germany S30810-Q2953-Xxx = Country var. | x | x | - | - | no | no | no | no | R10.0.0 | X | X |
| TLA8 Analog Trunk Line | S30817-H926-Axx = Country var. | x | x | - | - | X | X | X | X | X | X | |
| TS2 (Trunk Module S2M) | S30817-H2913-X100 | - | x | - | - | X | X | X | X | X | X | X |
| TS2 (Trunk Module S2M) new | S30810-H2913-X300 | - | x | - | - | no | no | no | X | X | X | X |
| SLC16 (old) Cordless | S30810-Q2922-X | - | x | - | - | X | X | X | X | no | no | no |
| SLC16N Cordless | S30810-Q2193-X100 | - | x | - | - | X | X | X | X | X | X | X |
| CBRC , Motherboard (as of issue E2 for 64MB MMC) | S30810-K2935-Z | - | - | x | x | | | X | no | no | no | |
| CBRC incl. EVM , Motherboard Ringing voltage (a/b) 35 V (as of issue C1 for 64MB MMC) | S30810-K2935-Z301 | - | - | x | x | | | | X | X | X | X |
| CBRC neu Integrated LIM and EVM, 1 x V24 Ringing voltage (a/b) 65 V | S30810-K2935-Z401 | - | - | x | x | | | | X | X | X | X |
| HXGSR2 LAN-Board HG1500 V2 | S30810-K2939-Z100 | - | - | x | x | | | | | | | |
| HXGSR3 LAN-Board HG1500 V3 | S30810-K2943-Z | - | - | x | x | | | V3.0 | V5.0 | V6.0 | V7.0 | V8 |
| HXGSR3 (new as of V8) LAN-Board HG1500 V3 | S30810-K2943-Z1 | - | - | x | x | | | no | X | X | X | V8 |
| IMODC analog mode up to 14.4 kbit/s | S30807-Q6932-X | x | x | x | x | X | X | X | X | X | X | X |
| IMODC analog mode up to 33.6 kbit/s | S30807-Q6932-X100 | x | x | x | x | X | X | X | X | X | X | X |
| IVMS8R HiPath Xpressions Compact V2.0 | S30122-K7379-Z | - | - | - | x | X | X | X | X | X | X | X |
| IVMP8R HiPath Xpressions Compact V2.0 | S30122-K7379-Z100 | - | - | x | - | | | X | X | X | X | X |

| | | | | | | | | | | | | | |
|---|--------------------------------------|---|---|---|---|----|----|----|----|--|----------------------------------|------------------------------|---|
| IVMP4R (4 Port) HiPath Xpressions Compact V2.5 (without hard disc) | S30122-K7721-X | - | - | x | x | | | | | | SMR8 | X | X |
| IVMS8NR (8 Port) HiPath Xpressions Compact V2.5 (with hard disc) | S30122-K7379-Z200 | - | - | x | x | | | | | | SMR8 | X | X |
| EVM , Entry Voice Mail | S30807-Q6945-X | x | x | x | x | | | | X | | X | X | X |
| UAM Announcement before Answering | S30122-X7217-X country variants | x | x | - | - | | | X | X | | X | X | X |
| OPALR Options Adapter Cable Long Rack) | C39195-A7001-B142 | - | - | x | x | | | X | X | | X | X | X |
| SLU8R Digitale Subscriber Line (U _{PN}) | (S30817-K922-Z301 | - | - | x | x | | | X | X | | X | X | X |
| STLS4R S0-Trunk- / Subscriber Line | S30817-K924-Z313 | - | - | x | x | | | | X | | X | X | |
| STLSX4R new S0-Trunk- / Subscriber Line | S30810-H2944-Z | - | - | x | x | | | | X | | X | X | X |
| STRBR Control Relay Board Rack | S30817-H932-Z | - | - | x | x | | | X | X | | X | X | X |
| TLA4R Analog Trunk Line | S30817-Q923-Zxxx country variants | - | - | x | x | | | X | X | | X | X | X |
| TLANI4R new Analog Trunk Line | S30810-Q2953-X2xx (X200 = GER) | - | - | x | x | no | no | no | no | | R10.0.0 | X | X |
| UAMR Announcement before Answering | S30122-X7402-Z | - | - | x | x | no | no | X | X | | X | X | X |
| 8SLAR Subscriber Line Analog Ringing voltage (a/b) 75 V | S30810-K2925-Z | - | - | x | x | no | no | X | X | | X | X | |
| SLADR8 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF- receiver | S30810-K2956-X300 | - | - | x | x | no | no | no | no | | X ab V6.0R11.1.0, bind 831 | X ab V7R4.3.0, bind 42 | X |
| EBR Extension-Box-Rack | S30777-U711-E901 | - | - | x | x | | | X | X | | X | X | X |
| EPSU2 external power supply unit | S30122-K7221-X2 | x | x | - | - | no | no | no | X | | X | X | X |
| EPSU2-R external power supply unit | | - | - | x | x | no | no | no | X | | X | X | X |